

# OTTO Accumulator gun Type HPS-6T



Accumulator gun for cartridges and aluminium foil bags up to 600 ml

HPS-6T

## Characteristics

- ▶ For aluminium foil bags up to 600 ml and for 280/290/300/310 ml cartridges
- ▶ Includes 2 Li-Ion batteries, 10.8 volts / 1.5 Ah
- ▶ Quick charger with state of charge indicator (charge time approx. 40 minutes)
- ▶ Including 2-piece professional pressure disc, white, for the complete emptying of film bags
- ▶ The return stop prevents the cartridge and bag from overflowing
- ▶ Securely packaged in a durable transport case
- ▶ Conform to RoHS
- ▶ CE-compliant



## Technical properties

Voltage Volt [V]	10,8
Capacity Ampere Hours [Ah]	1,5
Thrust force [kN]	5,0
Advance rate [mm/min.]	variabel bis zu 380
Cartridge size [ml]	280 (Koaxial) / 290 / 300 / 310
Aluminium foil bag size [ml]	400 /580 /600
Length [mm]	~ 5600
Width [mm]	~140
Height [mm]	~280 (incl. battery)
Weight [g]	~2440 (incl. battery)

## Important information

Please read the enclosed operating instructions with the safety instructions before commissioning. When processing coaxial cartridges, the advance rate of the pressure disc should be < 150 mm/min. This means using max. stage 2 on the setting wheel on the handle of the OTTO accumulator gun type HPS-4T and HPS-6T!

## Application information

Compatible with OTTO foil bags standard, long and no. 163  
 Compatible with OTTO car charger Li-Ion 12 volt  
 Also available as an accessory: OTTO Li-Ion battery 10.8 volt/1.5 Ah  
 Also available as an accessory: OTTO Quick charger with charge indicator

## Packaging

Order unit (OU)	Order code
1 piece	HPS-6T

**Hermann Otto GmbH**  
 Krankenhausstr. 14 | 83413 Fridolfing, Germany  
 ☎ +49 8684 908-0 | @ info@otto-chemie.de  
 www.otto-chemie.com

**Application advice**  
 ☎ +49 8684 908-4300  
 @ tae@otto-chemie.de



SEALING & BONDING

## **Safety precautions**

Do not charge the batteries at temperatures below 10°C or above 40°C.

## **Disposal**

Never dispose of the discharge device, the discharged material, cartridges and bags or batteries in the household trash. Instead, dispose of them according to the legal regulations in the country of operation!