

OTTO quick charging station with charge indicator for HPS

Accessories for OTTO Accumulator gun type HPS-4T/-6T

LADE-HPS

Characteristics

- ▶ Quick charging station for Li-Ion battery with 10.8 V
- ▶ Quick charging station with 30 minutes charging time
- ▶ Conform to RoHS

Standards and tests

- ▶ CE marked

Technical properties

Protection type according to DIN EN 60529 (VDE 0470)	IP30 // Classe 2
Input voltage Volt [V]	100 - 240
Input power Watt [W]	30
Input frequency Hertz [Hz]	~ 50 / 60
Output voltage Volt [V]	10,8
Output power Ampere [A]	2,0
Weight [g]	~ 502 brutto



Application information

Charging the battery with the quick charging station:

Do not charge the batteries at temperatures below 10°C or above 40°C

1. If the batteries are exposed to a temperature below +5°C, they must be warmed up to at least +10°C prior to charging.
2. Once the battery has fully charged, remove the charger plug from the mains. (Unplug the charger)
3. The charger should cool down for about 1 hour between two battery charges.
4. Only use the quick charger with the accumulator guns, type HPS-4T/-6T, and the associated batteries. Other chargers may destroy the battery and the charger.

Packaging

Order unit (OU)	Order code
1 piece	LADE-HPS

Safety precautions

Do not charge the batteries at temperatures below 10°C or above 40°C.